

Access 7 C Configuration

Conf_number	W/CD	Datalength	Parity	Invert ID	Re-read	Buzzer and LED	Pin-code	RS485 addr	RS232/USB	Timings			
										1	2	3	4
7 CW/C2	Wiegand	66-bit	on	off	3 sec	8	8 beep on	0	C2	640	640	640	640
7 CD	CD	64-bit	on	off	3 sec	8		0	C2	70	270	130	150
7 CW 26b	Wiegand	26-bit	on	off	3 sec	8	8 beep on	0	C2	100	2100	100	2100
7 CW s	Wiegand	66-bit	on	off	1 sec	8	8 beep on	0	C2	500	500	500	500
Conf_1	Wiegand	37-bit	on	off	3 sec	8	6 beep off	0	HID	500	500	500	500
Conf_2	Wiegand	66-bit	on	off	3 sec	8	4 beeb on	0	C2	500	500	500	500
Conf_3	Wiegand	34-bit	on	off	3 sec	8	8 beep on	0	C2	80	1000	80	1000
Conf_4	Wiegand	26-bit	on	off	3 sec	8	26 beep on	0	C2	100	2000	100	2000
Conf_5	Wiegand	26-bit	on	off	3 sec	8	4 beeb on	0	C2	100	1000	100	1000
Conf_6	Wiegand	26-bit	on	off	3 sec	8	8 beep on	0	C2	100	1000	100	1000
Conf_7	Wiegand	34-bit	on	off	3 sec	8	off	0	C2	100	1000	100	1000
Conf_8	CD	BCD 10	on	off	3 sec	8		0	C2	70	530	210	320
Conf_9	CD	BCD 13	on	off	3 sec	8		0	C2	110	700	300	400
Conf_10	Wiegand	34-bit	on	off	3 sec	8	8 beep on	0	C2	500	500	500	500
Conf_11	Wiegand	34-bit	on	off	3 sec	8	off	0	C2	500	500	500	500
Conf_12	Wiegand	32-bit	off	off	3 sec	8	8 beep on	0	C2	100	1000	100	1000
Conf_13	Wiegand	34-bit	on	off	3 sec	8	8 beep on	0	C2	70	940	70	940
Conf_14	Wiegand	66-bit	on	off	3 sec	8	off	0	C2	70	940	70	940
Conf_15	Wiegand	26-bit	on	off	3 sec	2	off	0	C2	100	1000	100	1000
Conf_16	CD	40-bit	on	off	3 sec	2	4 beeb on	0	C2	50	250	170	110
Conf_17	Wiegand	58-bit	on	off	3 sec	8	8 beep on	0	C2	70	940	70	940
Conf_18	Wiegand	50-bit	on	off	3 sec	8	8 beep on	0	C2	70	940	70	940
Conf_19	Wiegand	66-bit	on	off	3 sec	8	8 beep on	0	C2	100	900	100	900
Conf_20	Wiegand	32-bit	off	off	3 sec	8	8 beep on	0	C2	640	640	640	640
Conf_21	Wiegand	32-bit	off	off	1 sec	8	8 beep on	0	C2	70	2000	70	2000
Conf_22	Wiegand	32-bit	off	off	3 sec	6	8 beep on	0	C2	70	2000	70	2000
Conf_23	Wiegand	34-bit	on	off	3 sec	9	off	0	C2	100	1000	100	1000
Conf_24	Wiegand	34-bit	on	off	3 sec	0	off	0	C2	100	1000	100	1000
Conf_25	Wiegand	32-bit	off	off	3 sec	8	8 beep on	0	C2	70	2000	70	2000
Conf_26	CD	BCD 13 16 LZ	on	off	3 sec	6	4 beeb on	0	C2	150	850	420	420
Conf_27	Wiegand	32/56/64-bit	off	off	1 sec	8	8 beep on	0	C2	100	2000	100	2000

Conf_28	CD	64-bit	on	off	3 sec	0		0	C2	70	270	130	150
Conf_29	Wiegand	34-bit	on	off	0 sec	8	8 beep on	0	C2	80	1000	80	1000
Conf_30	Wiegand	56-bit	off	off	3 sec	8	8 beep on	0	C2	100	2000	100	2000
Conf_31	Wiegand	34-bit	on	off	3 sec	8	8 beep on	0	C2	100	1000	100	1000
Conf_32	CD	64-bit	on	off	3 sec	9	4 beeb on	0	C2	70	270	130	150
Conf_33	Wiegand	34-bit	on	off	3 sec	6	8 beep on	0	C2	100	1000	100	1000
Conf_34	Wiegand	66-bit	on	off	3 sec	2	8 beep on	0	C2	100	1000	100	1000
Conf_35	Wiegand	26-bit	on	off	3 sec	8	off	0	C2	50	2000	50	2000
Conf_36	Wiegand	64-bit	off	off	3 sec	8	8 beep on	0	C2	50	2000	50	2000
Conf_37	CD	40-bit	on	off	3 sec	8	8 beep on	0	C2	70	270	130	150
Conf_38	Wiegand	32-bit	off	off	3 sec	8	8 beep on	0	C2	70	930	70	930